

1984 - 1996 Corvette: Wiring and Circuit Identification

Below are tables showing the identification of wiring and circuits for 1984 - 1996 Corvettes:

| | |
|---|------------------|
| MODULE CONTROLLED LAMP OUT INDICATOR GRND | 256 DK BLUE |
| A/C PRESSURE SWITCH CONTROLLED GROUND | 257 BROWN |
| THEFT DETERRENT - HOOD SWITCH | 260 BLACK |
| THEFT DETERRENT - ALARM ARM | 261 YELLOW |
| THEFT DETERRENT - KEY DOOR UNLOCK | 262 LT GREEN |
| THEFT DETERRENT - ALARM | 263 LT BLUE |
| THEFT DETERRENT - ALARM INDICATION | 264 DK GREEN |
| THEFT DETERRENT - ALARM OUTPUT | 265 BLK/WHITE |
| THEFT DETERRENT - ALARM ARM ABORT | 266 PINK |
| POWER SEAT - FORE & UP RECLINER | 267 DK GREEN |
| POWER SEAT - AFT & DOWN RECLINER | 268 YELLOW |
| POWER SEAT - SOLENOID UP & DOWN RECLINER | 269 LT GREEN |
| AMPLIFIER TO POTENTIOMETER - FEED | 270 BLK/YELLOW |
| POTENTIOMETER CONTROLLED GROUND | 271 PURPLE |
| POTENTIOMETER RHEOSTAT CONTROLLED FEED | 272 LT GREEN |
| HEADLAMP SWITCH TO AMPLIFIER, HEADLAMP SWITCH CONTROLLED FEED | 273 ORANGE |
| HEADLAMP SWITCH TO AMPLIFIER - FEED | 274 DK GRN/WHITE |
| NEUTRAL SAFETY START SWITCH - PARK CONTROLLED FEED | 275 LT GRN/BLACK |
| POWER SEAT FORWARD - RECLINING MOTOR FEED | 276 LT GRN |
| POWER SEAT RECLINER - RECLINER MOTOR FEED | 277 LT BLUE |
| AMPLIFIER PHOTOCELL | 278 WHITE |
| HEADLAMP SWITCH TO PHOTOCELL | 279 BLACK |
| PERMANENT MAGNET MOTOR UP CYCLE (DECK LID PULL DOWN) FEED | 280 PINK |
| RELAY COIL DOWN CYCLE (DECK PULL DOWN) GRND | 281 WHITE |
| POWER SEAT, REAR VERTICAL UP MOTOR | 282 YELLOW |
| POWER SEAT, REAR VERTICAL DOWN MOTOR | 283 LT BLUE |
| POWER SEAT AFT MOTOR | 284 LT GREEN |
| POWER SEAT FORE MOTOR | 285 TAN |
| POWER SEAT FRONT VERTICAL UP MOTOR | 286 DK GREEN |
| POWER SEAT FRONT VERTICAL DOWN MOTOR | 287 DK BLUE |
| POWER SEAT REAR VERTICAL UP RELAY | 288 YELLOW/BLACK |

| | |
|---|----------------------|
| POWER SEAT REAR VERTICAL DOWN RELAY | 289 LT BLUE/BLACK |
| POWER SEAT AFT RELAY | 290 LT GRN/BLACK |
| HEATED GLASS, TIMER, ON-OFF SWITCH CONTROLLED GROUND | 291 DK BLUE |
| HEATED GLASS, TIMER, ON-OFF SWITCH CONTROLLED FEED | 292 LT BLUE |
| HEATED GLASS TIMER CONTROLLED FEED | 293 PURPLE/WHITE |
| DOOR LOCK MOTOR UNLOCK | 294 TAN |
| DOOR LOCK MOTOR LOCK | 295 GRAY |
| POWER SEAT FORE RELAY | 296 BROWN |
| POWER SEAT FRONT VERTICAL UP RELAY | 297 GRAY |
| POWER SEAT FRONT VERTICAL DOWN RELAY | 298 PURPLE |
| SEAT WARNING SYSTEM - DOOR RETRACTOR SWITCHED GROUND | 299 LT BLUE |
| IGNITION SWITCH "ON" CONTRLD UNFUSED FEED | 300 ORANGE |
| HEADLAMP ON WARNING 12 V FEED | 301 WHITE/BROWN |
| LOW VOLTAGE - SUB WOOFER SYSTEM | 302 WHITE |
| GAIN VOLTAGE - SUB WOOFER SYSTEM | 303 YELLOW |
| TWILIGHT SENTINEL ENABLE | 304 YELLOW/BLACK |
| 5 VOLTS REF - CRT FROM CONTRLR (LOW ENERGY) | 305 GRAY/RED |
| POTENTIOMETER CONTROLLED DIM SENSITIVITY GUIDEMATIC | 306 DARK GREEN |
| HIGH TO LOW BEAM SWITCH - FLASH TO PASS SIGNAL | 307 YELLOW/BLACK |
| PARK LIGHTS ON SENSE SIGNAL (TWILIGHT SENTINEL) | 308 GRAY/BLACK |
| RH INBOARD TAIL LAMP FEED (LAMP MONITOR) | 309 BROWN/WHITE |
| DIMMER SWITCH CONTROLLED FEED - GUIDEMATIC ENABLE | 310 YELLOW/BLACK |
| RIGHT HI BEAM FEED (LAMP MONITOR) | 311 LT GREEN/BLACK |
| RIGHT LOW BEAM FEED (LAMP MONITOR) | 312 TAN/WHITE |
| OIL PRESSURE SENDER ANALOG SIGNAL - LOW ENERGY | 313 LIGHT GREEN |
| 14 VOLT REF (REMOTE TAPE DECK) | 314 LT BLUE/BLACK |
| SUB-WOOFER SPEAKER; MINUS (-) OUTPUT & RADIO SPEAKER AMPLIFIER; RH DOOR RETURN | 315 LT BLUE/BLK |
| RELAY ACTIVATED LEFT DIRECTIONAL LAMP | 318 YELLOW/BLACK |
| RELAY ACTIVATED RIGHT DIRECTIONAL LAMP | 319 DARK GREEN/WHITE |
| ELECTRONIC LEVEL CONTROL - EXHAUST SOLENOID | 320 WHITE |
| ELECTRONIC LEVEL CONTROL - CONTROL RELAY | 321 YELLOW |
| ELECTRONIC LEVEL CONTROL - COMPRESSOR | 322 DARK GREEN |

| | |
|--|-----------------------|
| ECM TO SERVICE ELECTRICAL SYSTEM LAMP | 325 YELLOW |
| PHOTO AMPLIFIER HIGH-TO-LOW BEAM DIM OUTPUT | 328 PURPLE |
| RADIO SPEAKER AMPLIFIER - LEFT DOOR RETURN | 329 LIGHT GREEN/BLACK |
| RADIO SPEAKER AMPLIFIER - LEFT DOOR FEED | 330 LIGHT GREEN/WHITE |
| OIL PRESSURE TRANSDUCER | 331 TAN/WHITE |
| CRT RE IN FROM CONTROLLER | 332 DARK BLUE/ORANGE |
| LOW BRAKE VACUUM SWITCH CONTROLLED | 333 TAN |
| CRT WAKE-UP SIGNAL FROM CONTROLLER | 334 BLACK/LT BLUE |
| ELECTRIC COOLING FAN RELAY - COIL GROUND (A/C OR ENGINE TEMPERATURE) | 335 DK GREEN/WHITE |
| GUIDEMATIC POWER RELAY COIL FEED - PHOTO AMPLIFIER CONTROLLED | 338 PURPLE/WHITE |
| IGNITION SWITCH ON & CRANK CONTROLLED FUSE FEED | 339 PINK BLACK |
| BATTERY FUSE FEED | 340 ORANGE |
| SWITCH FEED - ENGINE SPEED SENSOR TO STEP SPEED CONTROL SOLENOID | 341 BROWN |
| ON & OFF CONTROLLED - UNFUSED | 342 LIGHT GREEN |
| ON & OFF CONTROLLED - UNFUSED | 343 WHITE |
| LOW ENERGY CIRCUIT KEYLESS ENTRY SWITCH PAD FEED FROM MODULE | 344 RED/BLACK |
| SUB-WOOFER SPEAKER : PLUS (+) OUTPUT & RADIO SPEAKER AMPLIFIER - LH DOOR FEED | 346 DK BLUE/WHITE |
| IGNITION SWITCH ON CONTROLLED FUSED FEED | 350 PINK/WHITE |
| LAMP FEED FROM ELECTROLUMINESCENCE INVERTER | 351 DK BLUE |
| LAMP GRND TO ELECTROLUMINESCENCE INVERTER | 352 WHITE |
| ANALOG "PRNDL" SIGNAL FROM TMNSS | 356 GRAY |
| LOW ENERGY CIRCUIT FEEDBACK SIGNAL FROM EVRV | 357 RED |
| FRONT RIGHT PARK LAMP FEED (LAMP MONITOR) | 359 PURPLE/YELLOW |
| AMPLIFIER FEED - RELAY BOSE SPEAKER SYSTEM | 360 ORANGE |
| PUSH BUTTON AIR CONDITION BI-LEVEL 12 V FEED | 361 PURPLE |
| PUSH BUTTON AIR CONDITION HEATER | 362 RED |
| PUSH BUTTON AIR CONDITION DEFROST | 363 TAN |
| AIR CONDITION CUT OUT SWITCH CONTROLLED | 366 LIGHT GREEN/BLACK |
| LOW ENERGY CIRCUIT LEFT AUDIO SIGNAL (REMOTE TAPE DECK) | 367 BROWN/WHITE |
| LOW ENERGY CIRCUIT RIGHT AUDIO SIGNAL (REMOTE TAPE DECK) | 368 DK GREEN/WHITE |
| AUTOMATIC VEHICLE LEVELING - FEED | 370 PINK |

| | |
|---|----------------------|
| LOW GROUND (REMOTE TAPE DECK) | 371 BLACK/ORANGE |
| HIGH GROUND (REMOTE TAPE DECK) | 372 BLACK/WHITE |
| FUEL USED SIGNAL (DIGITAL DISPLAY) | 374 BROWN |
| FUEL READOUT RESET (DIGITAL DISPLAY) | 375 PINK |
| TRIP RESET (DIGITAL DISPLAY) | 376 LIGHT GREEN |
| DIAGNOSTIC ENABLE (DIGITAL DISPLAY) | 377 PURPLE |
| 3-MODE ELECTRONIC CRUISE - CRUISE SPEED SIGNAL | 381 RED |
| CONVERT CLUTCH RELEASE SWITCH TO VACUUM SWITCH | 383 LIGHT BLUE |
| VACUUM SWITCH TO TRANSMISSION SWITCH SOLENOID | 384 LIGHT GREEN |
| HIGH VACUUM SWITCH TO TRANSMISSION SWITCH SOLENOID | 385 PURPLE |
| EGR BLEED SOLENOID TO TCC PRESSURE SWITCH | 386 YELLOW |
| TCC PRESSURE SWITCH TO TRANSMISSION SOLENOID | 387 ORANGE |
| TCC COOLANT SWITCH TO LOW VACUUM SWITCH | 388 WHITE |
| 3-MODE ELECTRONIC CRUISE - SPEEDO SPEED SIGNAL | 389 DARK GREEN |
| SIDE MARKER & LICENSE LAMP (EXPORT MODEL) | 390 TAN |
| 3-MODE ELECTRONIC CRUISE - ON/OFF SWITCH | 397 GRAY |
| 3-MODE ELECTRONIC CRUISE - SERVO POSITION SENSOR - HIGH | 398 TAN |
| 3-MODE ELECTRONIC CRUISE - SERVO POSITION SENSOR - LOW | 399 LIGHT BLUE/BLACK |
| ELECTRONIC CRUISE CONTROL VACUUM VALVE FEED | 402 LIGHT GREEN |
| ELECTRONIC CRUISE CONTROL VENT VALVE FEED | 403 DK BLUE/WHITE |
| LOW ENERGY EST PICKUP COIL TO HEI MODULE | 405 WHITE |
| LOW ENERGY ESC MODULE TO HEI MODULE SIGNAL LEAD | 405 WHITE/DK GREEN |
| LOW ENERGY ECM TO HEI MODULE - EMR SIGNAL LEAD | 407 BLACK |
| LOW ENERGY ECM TO ESC BYPASS | 408 TAN/WHITE |
| COOLANT FAN CONTROL FUSED FEED | 409 LT BLUE/BLACK |

Online URL:

<https://www.corvetteactioncenter.com/tech/knowledgebase/article/1984-1996-corvette-wiring-and-circuit-identification-1163.html>